JPD-500D

Pulse Oximeter



- Integrated with SPO_2 probe and processing display module.
- Small in volume、light in weight and convenient in carrying.
- Operation of the product is simple ,low power consumption.
- SPO_2 , PR and RIdisplay,
- Pulse rate value display, bar graph display.
- Low-voltage indication: low-voltage indicator appears before working abnormally which is due to low-voltage.
- Automatically power off function: when the device is under the state of measuring interface .
- Various color of cover can be selected.
- Auto shut off :10s
- OLED display,Adjustable brightness
- SPO_2 : 35-100%
- Pulse Ratio : 25-250BPM
- Resolution: 1% for SPO_2, 1BPM for pulse ratio
- Accuracy: ±1% (70%-100%) ,
  unspecified (<70%) for SPO_2,
  ±1BPM or±1% (select larger) for pulse ratio
- Power: 1.5V (AAA size) alkaline batteries × 2
- Size：62. 2×37. 0×33. 1mm